







GO TO PRODUCT

- EMC-compliant radio-frequency transfers for connecting highly sensitive PCBs to the measuring system, from and into the shielding area
- Interference-free transmission of low voltage and serial signals
- Capacity 830 pF
- 50 mating cycles



Application

The radio-frequency transfer with integrated interference suppression filter (8 MHz - 3 dB) is used to transmit low-voltage and serial signals from and into the radio-frequency chamber. The filter with a capacitance of 830 pF ensures that unwanted signals cannot pass through the shielding area.



General data

Product group:

Series:

Type:

Version:

Accessory type:

Scope of delivery:

Weight:

Min. temperature:

Max. temperature:

RoHS-compliant:

RF accessories

HF-U

RF transfer

D-sub plug connector

Customising accessories

Unassembled

0.04 kg [.088 lbs]

-25 °C [-13 °F]

85 °C [185 °F]

Yes

Compatible with

Exchangeable kits version:

MA exchangeable kits (ATS MA):

HF

ATS MAxx/HF/AL/ESD

Technical data

Connection:

Max. current:

Max. voltage:

Contact resistance:

Number of poles:

Capacity:

Wire-wrap posts

7.5 A

100 VDC

10 mOhm

37

830 pF

RF transfer

HF-U-SUBD-37-830pF-WW



Item 53085



GO TO PRODUCT

ingun[®]

Partner for Future Technology



Technical information	
Designation	Version
Filter	LC circuit
Insertion force	170 N
Extraction force	170 N
Attenuation (8 MHz)	3 dB (typisch)

INGUN Prüfmittelbau GmbH

Max-Stromeyer-Straße 162
78467, Constance, Germany
Phone +49 7531 8105-0
Customer hotline +49 7531 8105-888
Fax +49 7531 8105-65
info@ingun.com



Prices and delivery times on request.
Technical changes reserved. 11/25_GB