








- EMC-compliant radio-frequency transfers for connecting highly sensitive PCBs to the measuring system, from and into the shielding area
- Interference-free transmission of low voltage and serial signals
- Capacity 830 pF
- 50 mating cycles



Application

The radio-frequency transfer with integrated interference suppression filter (8 MHz - 3 dB) is used to transmit low-voltage and serial signals from and into the radio-frequency chamber. The filter with a capacitance of 830 pF ensures that unwanted signals cannot pass through the shielding area.



General data

Product group:
Series:
Type:
Version:
Accessory type:
Scope of delivery:
Weight:
Min. temperature:
Max. temperature:
RoHS-compliant:

RF accessories
HF-U
RF transfer
D-sub plug connector
Customising accessories
Unassembled
0.04 kg [.088 lbs]
-25 °C [-13 °F]
85 °C [185 °F]
Yes

Compatible with



Exchangeable kits version:
MA exchangeable kits (ATS MA):

HF
ATS MAxx/HF/AL/ESD

Technical data

Connection:
Max. current:
Max. voltage:
Contact resistance:
Number of poles:
Capacity:

Wire-wrap posts
7.5 A
100 VDC
10 mOhm
50
830 pF



Technical information	
Designation	Version
Filter	LC circuit
Insertion force	170 N
Extraction force	170 N
Attenuation (8 MHz)	3 dB (typisch)

INGUN Prüfmittelbau GmbH

Max-Stromeyer-Straße 162
 78467, Constance, Germany
 Phone +49 7531 8105-0
 Customer hotline +49 7531 8105-888
 Fax +49 7531 8105-65
info@ingun.com

